Aspirator2

The SmartBarrel Aspirator2 is used to evacuate headspace and take samples from all SmartBarrel and GOfermentor liners. Suction operation eliminates risk of contamination. Cordless operation features 3 speeds to regulate the suction. Press the power button to cycle from low to high and off, indicated by a blue LED. The twist-off collection cup can hold up to 300 mL. Overflow shutoff prevents spillage if left unattended.

Evacuating headspace in SmartBarrel liners:

Gases trapped in the headspace of the liners must be removed to avoid degrading the wine. Gases can enter during filling, or form due to secondary fermentation.
Connect the aspirator to the sampling port of the SmartBarrel diptube and press the power button until all gases are removed. Pull up the liner near the end to remove trapped gases. Disconnect the tube quickconnect fitting from the liner sampling port with the aspirator still running. This stops spillage during disconnect.

Cordless aspirator sampler

Sampling from SmartBarrel or GOfermentor Fermentation Liners:

To draw a sample, attach the hose to the sampling port and run until desired amount is collected. Disconnect from the sampling port with the aspirator still running to reduce spillage. Twist off the sampling cup to analyze the sample collected

Cleaning the Unit:

To clean the tubing and inlet, attach the empty collection cup, dip end of sampling tube in a small container with warm water or cleaning solution. Run the unit to rinse. Tubing should be disconnected to hang dry for storage. To clean the collection cup, remove it to rinse. The pump housing cannot be immersed in water, only wipe the surfaces to clean.
When reattaching collection cup, pay attention to thread correctly and an even seal is made with the gasket. This seal is necessary for the device to pull a suction.

Charging the Unit:

To charge, insert the supplied USB-C cable in to the charging port just below the power button. Connect cable to a standard 5V USB power supply, such as a phone charger. The power button will illuminate red while charging, green when fully charged. Battery run time 3 hours. A slow blinking red indicates low battery charge.

Support: www.GOfermentor.com

tech@GOfermentor.com

Version 1.4 TR 10/26